

**Topic:** Resetting Security Settings  
**Component(s) Affected:** ClearCube Blades, Windows XP  
**Date:** April 2, 2005

---

## OVERVIEW / ENVIRONMENT

---

When a system using ClearCube software is configured as a member of a workgroup, moved to a domain, and then moved back to a workgroup (either the same workgroup or a new one), network connectivity is lost until that system's security settings are returned to their default.

This Technical Bulletin describes how to set the security settings back to the default settings.

---

## DETAILED DESCRIPTION

---

If you configure a Blade using ClearCube software as a member of a workgroup, move the system to a domain, and then move the system back to a workgroup (either the same workgroup or a new one), network connectivity is lost until that system's security settings are returned to their default.

To reset the system to its default security setting, do the following:

1. Enter the following at a command prompt:

```
secedit /configure /cfg %windir% \repair\secsetup.inf /db secsetup.sdb /verbose
```

2. You receive a `Task is completed` message and a warning message that something could not be done. You can safely ignore the warning message.

For more information about the warning message, view the `%windir%\Security\Logs\Scesrv.log` file.

This is a known issue with Windows, and is documented in Microsoft's Knowledge Base as article 313222, found at:

<http://support.microsoft.com/?kbid=313222>

To contact ClearCube technical support:

[support@clearcube.com](mailto:support@clearcube.com)  
[support.clearcube.com](http://support.clearcube.com)  
(866) 652-3400  
+1 (512) 652-3400

Email address for ClearCube Technical Support  
ClearCube Support Website  
Direct line in the US  
Direct line from outside the US