

BIOS Update Instructions

Model - R1150




R1150-S19 BIOS Fixes and Enhancements:

BIOS R1150-S19 fixes invalid entries in the Windows XP Event Viewer. The error entry is displayed in the Event Viewer as ***“ACPI BIOS is attempting to read from an illegal IO port address (0xcfc), which lies in the 0xcf8 - 0xcff protected address range. This could lead to system instability. Please contact your system vendor for technical assistance”***.

Requirements for updating your Bios:

- USB Floppy Drive
- DOS Bootable Floppy Disk
- BIOS Update (R1150-S19.exe)

Please follow the instructions in order to update the BIOS on your R-Series blade:

Step 1) Create a DOS Bootable Floppy.	
Step 2) Download the R1150-S19 BIOS update from http://support.clearcube.com/hardware.htm .	
Step 3) Double Click the downloaded bios update from the saved location on your computer.	
Step 4) From the WinZip Self-Extractor dialog, click the Unzip Button. <i>(Make sure the DOS Bootable floppy is inserted the USB floppy drive)</i>	
Step 5) When the message "# file(s) unzipped successfully" appears click the OK button	
Step 6) From the WinZip Self-Extractor dialog click the close button.	
Step 7) With the floppy disk in, restart your computer.	
Step 8) Upon restart, the computer will boot from the floppy driver and automatically update the motherboard's BIOS. Follow the onscreen instructions.	
If you have any problems during the update process please call ClearCube Support at 866-652-3400 or e-mail support@clearcube.com for assistance.	

0205040J